

Condensador de potencia trifásico BSMJ tipo caja 0,45 / 0,48 / 0,525 kV Condensadores paralelos de bajo voltaje autorreparables

| Rated Voltage (kV) | Rated Output (kvar) | Rated Capacitor (µF) | Rated Current (A) | H (mm) | Output Terminal | Shell Type | Model BSMJ | Model BCMJ | Model BZMJ |
|--------------------|---------------------|----------------------|-------------------|---------|-----------------|------------|-----------------|-----------------|-----------------|
| 0.4 | 1 | 19.9 | 1.4 | 105 | M6 | A1 | BSMJ-0.4-1-3 | BCMJ-0.4-1-3 | BZMJ-0.4-1-3 |
| 0.4 | 2 | 39.8 | 2.9 | 105 | M6 | A1 | BSMJ-0.4-2-3 | BCMJ-0.4-2-3 | BZMJ-0.4-2-3 |
| 0.4 | 3 | 59.7 | 4.3 | 125 | M6 | A2 | BSMJ-0.4-3-3 | BCMJ-0.4-3-3 | BZMJ-0.4-3-3 |
| 0.4 | 4 | 79.6 | 5.8 | 125 | M6 | A2 | BSMJ-0.4-4-3 | BCMJ-0.4-4-3 | BZMJ-0.4-4-3 |
| 0.4 | 5 | 99.5 | 7.2 | 125 | M6 | A2 | BSMJ-0.4-5-3 | BCMJ-0.4-5-3 | BZMJ-0.4-5-3 |
| 0.4 | 6 | 119.4 | 8.7 | 125 | M6 | A2 | BSMJ-0.4-6-3 | BCMJ-0.4-6-3 | BZMJ-0.4-6-3 |
| 0.4 | 7.5 | 149.2 | 10.8 | 125 | M6 | A2 | BSMJ-0.4-7.5-3 | BCMJ-0.4-7.5-3 | BZMJ-0.4-7.5-3 |
| 0.4 | 8 | 159.2 | 11.6 | 125 | M6 | A2 | BSMJ-0.4-8-3 | BCMJ-0.4-8-3 | BZMJ-0.4-8-3 |
| 0.4 | 10 | 198.9 | 14.4 | 180 | M6 | A2 | BSMJ-0.4-10-3 | BCMJ-0.4-10-3 | BZMJ-0.4-10-3 |
| 0.4 | 12 | 238.7 | 17.3 | 180 | M6 | A2 | BSMJ-0.4-12-3 | BCMJ-0.4-12-3 | BZMJ-0.4-12-3 |
| 0.4 | 14 | 278.5 | 20.2 | 210 | M6 | A2 | BSMJ-0.4-14-3 | BCMJ-0.4-14-3 | BZMJ-0.4-14-3 |
| 0.4 | 15 | 298.4 | 21.7 | 210 | M6 | A2 | BSMJ-0.4-15-3 | BCMJ-0.4-15-3 | BZMJ-0.4-15-3 |
| 0.4 | 16 | 318.3 | 23.1 | 210 | M6 | A2 | BSMJ-0.4-16-3 | BCMJ-0.4-16-3 | BZMJ-0.4-16-3 |
| 0.4 | 18 | 358.1 | 26.0 | 245/210 | M6 | A2/B2 | BSMJ-0.4-18-3 | BCMJ-0.4-18-3 | BZMJ-0.4-18-3 |
| 0.4 | 20 | 397.9 | 28.9 | 245/210 | M6 | A2/B2 | BSMJ-0.4-20-3 | BCMJ-0.4-20-3 | BZMJ-0.4-20-3 |
| 0.4 | 22 | 437.7 | 31.8 | 210 | M8 | B2 | BSMJ-0.4-22-3 | BCMJ-0.4-22-3 | BZMJ-0.4-22-3 |
| 0.4 | 24 | 477.5 | 34.6 | 210 | M8 | B2 | BSMJ-0.4-24-3 | BCMJ-0.4-24-3 | BZMJ-0.4-24-3 |
| 0.4 | 25 | 497.4 | 36.1 | 210 | M8 | B2 | BSMJ-0.4-25-3 | BCMJ-0.4-25-3 | BZMJ-0.4-25-3 |
| 0.4 | 28 | 557.3 | 40.4 | 260 | M8 | B2 | BSMJ-0.4-28-3 | BCMJ-0.4-28-3 | BZMJ-0.4-28-3 |
| 0.4 | 30 | 596.8 | 43.3 | 260 | M8 | B2 | BSMJ-0.4-30-3 | BCMJ-0.4-30-3 | BZMJ-0.4-30-3 |
| 0.4 | 35 | 696.3 | 50.5 | 260 | M8 | B2 | BSMJ-0.4-35-3 | BCMJ-0.4-35-3 | BZMJ-0.4-35-3 |
| 0.4 | 40 | 796.2 | 57.7 | 320 | M8 | B2 | BSMJ-0.4-40-3 | BCMJ-0.4-40-3 | BZMJ-0.4-40-3 |
| 0.4 | 45 | 895.2 | 65.0 | 210 | M10 | C | BSMJ-0.4-45-3 | BCMJ-0.4-45-3 | BZMJ-0.4-45-3 |
| 0.4 | 50 | 995.2 | 72.2 | 210 | M10 | C | BSMJ-0.4-50-3 | BCMJ-0.4-50-3 | BZMJ-0.4-50-3 |
| 0.4 | 55 | 1094.2 | 79.4 | 260 | M10 | C | BSMJ-0.4-55-3 | BCMJ-0.4-55-3 | BZMJ-0.4-55-3 |
| 0.4 | 60 | 1194.3 | 86.6 | 260 | M10 | C | BSMJ-0.4-60-3 | BCMJ-0.4-60-3 | BZMJ-0.4-60-3 |
| 0.45 | 1 | 15.7 | 1.3 | 105 | M6 | A1 | BSMJ-0.45-1-3 | BCMJ-0.45-1-3 | BZMJ-0.45-1-3 |
| 0.45 | 2 | 31.4 | 2.6 | 105 | M6 | A1 | BSMJ-0.45-2-3 | BCMJ-0.45-2-3 | BZMJ-0.45-2-3 |
| 0.45 | 3 | 47.2 | 3.8 | 125 | M6 | A2 | BSMJ-0.45-3-3 | BCMJ-0.45-3-3 | BZMJ-0.45-3-3 |
| 0.45 | 4 | 62.9 | 5.1 | 125 | M6 | A2 | BSMJ-0.45-4-3 | BCMJ-0.45-4-3 | BZMJ-0.45-4-3 |
| 0.45 | 5 | 78.6 | 6.4 | 125 | M6 | A2 | BSMJ-0.45-5-3 | BCMJ-0.45-5-3 | BZMJ-0.45-5-3 |
| 0.45 | 6 | 94.3 | 7.7 | 125 | M6 | A2 | BSMJ-0.45-6-3 | BCMJ-0.45-6-3 | BZMJ-0.45-6-3 |
| 0.45 | 7.5 | 117.9 | 9.6 | 125 | M6 | A2 | BSMJ-0.45-7.5-3 | BCMJ-0.45-7.5-3 | BZMJ-0.45-7.5-3 |
| 0.45 | 8 | 125.8 | 10.3 | 125 | M6 | A2 | BSMJ-0.45-8-3 | BCMJ-0.45-8-3 | BZMJ-0.45-8-3 |
| 0.45 | 10 | 157.2 | 12.8 | 180 | M6 | A2 | BSMJ-0.45-10-3 | BCMJ-0.45-10-3 | BZMJ-0.45-10-3 |
| 0.45 | 12 | 188.6 | 15.4 | 180 | M6 | A2 | BSMJ-0.45-12-3 | BCMJ-0.45-12-3 | BZMJ-0.45-12-3 |
| 0.45 | 14 | 220.1 | 18.0 | 210 | M6 | A2 | BSMJ-0.45-14-3 | BCMJ-0.45-14-3 | BZMJ-0.45-14-3 |
| 0.45 | 15 | 235.8 | 19.2 | 210 | M6 | A2 | BSMJ-0.45-15-3 | BCMJ-0.45-15-3 | BZMJ-0.45-15-3 |
| 0.45 | 16 | 251.5 | 20.5 | 210 | M6 | A2 | BSMJ-0.45-16-3 | BCMJ-0.45-16-3 | BZMJ-0.45-16-3 |
| 0.45 | 18 | 282.9 | 23.1 | 245/210 | M6 | A2/B2 | BSMJ-0.45-18-3 | BCMJ-0.45-18-3 | BZMJ-0.45-18-3 |
| 0.45 | 20 | 314.4 | 25.7 | 245/210 | M6 | A2/B2 | BSMJ-0.45-20-3 | BCMJ-0.45-20-3 | BZMJ-0.45-20-3 |
| 0.45 | 22 | 345.8 | 28.3 | 210 | M8 | B2 | BSMJ-0.45-22-3 | BCMJ-0.45-22-3 | BZMJ-0.45-22-3 |
| 0.45 | 24 | 377.3 | 30.8 | 210 | M8 | B2 | BSMJ-0.45-24-3 | BCMJ-0.45-24-3 | BZMJ-0.45-24-3 |
| 0.45 | 25 | 393.2 | 32.1 | 210 | M8 | B2 | BSMJ-0.45-25-3 | BCMJ-0.45-25-3 | BZMJ-0.45-25-3 |
| 0.45 | 28 | 440.3 | 35.9 | 210 | M8 | B2 | BSMJ-0.45-28-3 | BCMJ-0.45-28-3 | BZMJ-0.45-28-3 |
| 0.45 | 30 | 471.8 | 38.5 | 210 | M8 | B2 | BSMJ-0.45-30-3 | BCMJ-0.45-30-3 | BZMJ-0.45-30-3 |
| 0.45 | 35 | 550.2 | 44.9 | 260 | M8 | B2 | BSMJ-0.45-35-3 | BCMJ-0.45-35-3 | BZMJ-0.45-35-3 |
| 0.45 | 40 | 629.1 | 51.3 | 260 | M8 | B2 | BSMJ-0.45-40-3 | BCMJ-0.45-40-3 | BZMJ-0.45-40-3 |
| 0.45 | 45 | 707.4 | 57.7 | 210 | M10 | C | BSMJ-0.45-45-3 | BCMJ-0.45-45-3 | BZMJ-0.45-45-3 |
| 0.45 | 50 | 786.3 | 64.2 | 210 | M10 | C | BSMJ-0.45-50-3 | BCMJ-0.45-50-3 | BZMJ-0.45-50-3 |
| 0.45 | 55 | 864.5 | 70.6 | 210 | M10 | C | BSMJ-0.45-55-3 | BCMJ-0.45-55-3 | BZMJ-0.45-55-3 |
| 0.45 | 60 | 943.6 | 77.0 | 210 | M10 | C | BSMJ-0.45-60-3 | BCMJ-0.45-60-3 | BZMJ-0.45-60-3 |
| 0.525 | 5 | 57.7 | 5.5 | 125 | M6 | A2 | BSMJ-0.525-5-3 | BCMJ-0.525-5-3 | BZMJ-0.525-5-3 |

| Rated Voltage (kV) | Rated Output (kvar) | Rated Capacitor (uF) | Rated Current (A) | H (mm) | Output Terminal | Shell Type | Model BSMJ | Model BCMJ | Model BZMJ |
|--------------------|---------------------|----------------------|-------------------|--------|-----------------|------------|-----------------|-----------------|-----------------|
| 0.525 | 10 | 115.5 | 11.0 | 180 | M6 | A2 | BSMJ-0.525-10-3 | BCMJ-0.525-10-3 | BZMJ-0.525-10-3 |
| 0.525 | 15 | 173.2 | 16.5 | 210 | M6 | A2 | BSMJ-0.525-15-3 | BCMJ-0.525-15-3 | BZMJ-0.525-15-3 |
| 0.525 | 16 | 184.8 | 17.6 | 210 | M6 | A2 | BSMJ-0.525-16-3 | BCMJ-0.525-16-3 | BZMJ-0.525-16-3 |
| 0.525 | 18 | 207.9 | 19.8 | 210 | M6 | B2 | BSMJ-0.525-18-3 | BCMJ-0.525-18-3 | BZMJ-0.525-18-3 |
| 0.525 | 20 | 231.0 | 22.0 | 210 | M6 | B2 | BSMJ-0.525-20-3 | BCMJ-0.525-20-3 | BZMJ-0.525-20-3 |
| 0.525 | 25 | 288.7 | 27.5 | 210 | M8 | B2 | BSMJ-0.525-25-3 | BCMJ-0.525-25-3 | BZMJ-0.525-25-3 |
| 0.525 | 30 | 346.5 | 33.0 | 260 | M8 | B2 | BSMJ-0.525-30-3 | BCMJ-0.525-30-3 | BZMJ-0.525-30-3 |
| 0.525 | 40 | 461.9 | 44.0 | 320 | M8 | B2 | BSMJ-0.525-40-3 | BCMJ-0.525-40-3 | BZMJ-0.525-40-3 |
| 0.525 | 50 | 577.4 | 55.0 | 210 | M10 | C | BSMJ-0.525-50-3 | BCMJ-0.525-50-3 | BZMJ-0.525-50-3 |
| 0.525 | 60 | 692.9 | 66.0 | 260 | M10 | C | BSMJ-0.525-60-3 | BCMJ-0.525-60-3 | BZMJ-0.525-60-3 |
| 0.69 | 5 | 33.4 | 4.2 | 125 | M6 | A2 | BSMJ-0.69-5-3 | BCMJ-0.69-5-3 | BZMJ-0.69-5-3 |
| 0.69 | 10 | 66.9 | 8.4 | 180 | M6 | A2 | BSMJ-0.69-10-3 | BCMJ-0.69-10-3 | BZMJ-0.69-10-3 |
| 0.69 | 15 | 100.3 | 12.6 | 210 | M6 | A2 | BSMJ-0.69-15-3 | BCMJ-0.69-15-3 | BZMJ-0.69-15-3 |
| 0.69 | 16 | 107.0 | 13.4 | 210 | M6 | A2 | BSMJ-0.69-16-3 | BCMJ-0.69-16-3 | BZMJ-0.69-16-3 |
| 0.69 | 20 | 133.8 | 16.7 | 210 | M6 | B2 | BSMJ-0.69-20-3 | BCMJ-0.69-20-3 | BZMJ-0.69-20-3 |
| 0.69 | 25 | 167.2 | 20.9 | 210 | M6 | B2 | BSMJ-0.69-25-3 | BCMJ-0.69-25-3 | BZMJ-0.69-25-3 |
| 0.69 | 30 | 200.7 | 25.1 | 260 | M8 | B2 | BSMJ-0.69-30-3 | BCMJ-0.69-30-3 | BZMJ-0.69-30-3 |
| 0.69 | 40 | 267.4 | 33.5 | 320 | M8 | B2 | BSMJ-0.69-40-3 | BCMJ-0.69-40-3 | BZMJ-0.69-40-3 |
| 0.69 | 50 | 334.3 | 41.9 | 210 | M10 | C | BSMJ-0.69-50-3 | BCMJ-0.69-50-3 | BZMJ-0.69-50-3 |
| 0.69 | 60 | 401.1 | 50.2 | 260 | M10 | C | BSMJ-0.69-60-3 | BCMJ-0.69-60-3 | BZMJ-0.69-60-3 |
| 1.2 | 5 | 11.0 | 2.4 | 180 | M6 | A2 | BSMJ-1.2-5-3 | BCMJ-1.2-5-3 | BZMJ-1.2-5-3 |
| 1.2 | 10 | 22.0 | 4.8 | 210 | M6 | A2 | BSMJ-1.2-10-3 | BCMJ-1.2-10-3 | BZMJ-1.2-10-3 |
| 1.2 | 15 | 33.2 | 7.2 | 245 | M6 | A2 | BSMJ-1.2-15-3 | BCMJ-1.2-15-3 | BZMJ-1.2-15-3 |
| 1.2 | 20 | 44.2 | 9.6 | 210 | M6 | B2 | BSMJ-1.2-20-3 | BCMJ-1.2-20-3 | BZMJ-1.2-20-3 |
| 1.2 | 25 | 55.3 | 12 | 210 | M6 | B2 | BSMJ-1.2-25-3 | BCMJ-1.2-25-3 | BZMJ-1.2-25-3 |
| 1.2 | 30 | 66.3 | 14.4 | 210 | M10 | C | BSMJ-1.2-30-3 | BCMJ-1.2-30-3 | BZMJ-1.2-30-3 |
| 1.2 | 40 | 88.4 | 19.2 | 210 | M10 | C | BSMJ-1.2-40-3 | BCMJ-1.2-40-3 | BZMJ-1.2-40-3 |
| 1.2 | 50 | 110.5 | 24.1 | 210 | M10 | C | BSMJ-1.2-50-3 | BCMJ-1.2-50-3 | BZMJ-1.2-50-3 |

NANTONG HUASING ELECTRONICS CO.,LTD.

Email: sales@hua-sing.com

Http://www.hua-sing.com